

P19913.P03

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant :S.K. HUI

Appl No. : Not Yet Assigned

PCT Branch

I.A. Filed :November 12, 1999

PCT/SG99/00119

For :SIGNAL PROCESSING APPARATUS

CLAIM OF PRIORITY

Commissioner of Patents and Trademarks

Washington, D.C. 20231

Sir:

Applicant hereby claims the right of priority granted pursuant to 35 U.S.C. 119 based upon Singapore Application No. 9804034-8, filed November 13, 1998. The International Bureau already should have sent a certified copy of the Singapore application to the United States designated office. If the certified copy has not arrived, please contact the undersigned.

Respectfully submitted,
S.K. HUI

Leslie J. Bernstein Reg. No. 33,329
Bruce H. Bernstein
Reg. No. 29,027

May 10, 2001
GREENBLUM & BERNSTEIN, P.L.C.
1941 Roland Clarke Place
Reston, VA 20191
(703) 716-1191

THIS PAGE BLANK (USPTO)

FOI/30 99.7 00119
09/831346


SG 99/119. **REGISTRY OF PATENTS
SINGAPORE**

REC'D 09 DEC 1999	
WIPO	PCT

⁴
This is to certify that the annexed is a true copy of the following Singapore patent application as filed in this Registry.

Date of Filing : 13 NOVEMBER 1998
Application number : 9804034-8
Applicants : BITWAVE PRIVATE LIMITED
Title of Invention : SIGNAL PROCESSING APPARATUS AND METHOD

I further certify that the annexed documents are not, as yet, open to public inspection.



Liew Woon Yin (Ms)
Registrar of Patents
Singapore

24 November 1999


PRIORITY DOCUMENT
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH
RULE 17.1(a) OR (b)

SINGAPORE
THE PATENTS ACT
(CHAPTER 221)
THE PATENTS RULES

The Registrar of Patents
Registry of Patents

REQUEST FOR THE GRANT OF A PATENT

THE GRANT OF A PATENT IS REQUESTED BY THE UNDERSIGNED ON THE BASIS OF
THE PRESENT APPLICATION.



I. Title of Invention	SIGNAL PROCESSING APPARATUS AND METHOD			
II. Applicant (s) (See note 2)	(a) Name	BITWAVE PRIVATE LIMITED		
	Body Description / Residency	a company organized and existing under the laws of Singapore		
	Street Name & Number	10 Science Park Road #03-20, The Alpha, Singapore Science Park II		
	City			
	State			
	Country	Singapore 117684		
	(b) Name			
	Body Description / Residency			
	Street Name & Number			
	City			
	State			
	Country			
	(c) Name			
	Body Description / Residency			
	Street Name & Number			
	City			
	State			
	Country			
III. Declaration of priority (see note 3)	Country / Country Designated		File No.	
	Filing Date			
	Country / Country Designated		File No.	
	Filing Date			
	Country / Country Designated		File No.	
	Filing Date			

9804034-8

Inventors <i>(See note 4)</i> (a) The applicant(s) is/are the sole/joint inventor(s). (b) A statement on Patents Form 8 is/will be furnished.	<div style="display: flex; justify-content: space-around; align-items: center;"> <div><input type="checkbox"/> YES</div> <div><input checked="" type="checkbox"/> NO</div> </div> <div style="display: flex; justify-content: space-around; align-items: center;"> <div><input checked="" type="checkbox"/> YES</div> <div><input type="checkbox"/> NO</div> </div>																		
V. Name of Agent (if any) <i>(See note 5)</i>	LLOYD WISE																		
VI. Address for Service <i>(See note 6)</i>	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 25%;">Block/Hse No</td> <td style="width: 25%;"></td> <td style="width: 25%;">Level No</td> <td style="width: 25%;"></td> </tr> <tr> <td>Unit No/PO Box</td> <td>P O BOX 636</td> <td>Postal Code</td> <td>910816</td> </tr> <tr> <td>Street Name</td> <td colspan="3"></td> </tr> <tr> <td>Building Name</td> <td colspan="3">TANJONG PAGAR POST OFFICE</td> </tr> </table>	Block/Hse No		Level No		Unit No/PO Box	P O BOX 636	Postal Code	910816	Street Name				Building Name	TANJONG PAGAR POST OFFICE				
	Block/Hse No		Level No																
	Unit No/PO Box	P O BOX 636	Postal Code	910816															
	Street Name																		
Building Name	TANJONG PAGAR POST OFFICE																		
VII. Claiming an earlier filing date under section 20 (3), 26(6) or 47(4) <i>(see note 7)</i>	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 25%;">Application No</td> <td colspan="3"></td> </tr> <tr> <td>Filing Date</td> <td></td> <td></td> <td></td> </tr> </table>	Application No				Filing Date													
Application No																			
Filing Date																			
VIII. Invention has been displayed at an International Exhibition <i>(See note 8)</i>	<div style="display: flex; justify-content: space-around; align-items: center;"> <div><input type="checkbox"/> YES</div> <div><input checked="" type="checkbox"/> NO</div> </div>																		
IX. Section 114 requirements <i>(See note 9)</i>	The invention relates to and/or uses a micro-organism deposited for the purposes of disclosure in accordance with section 114 with a depositary authority under the Budapest Treaty. <div style="display: flex; justify-content: space-around; align-items: center;"> <div><input type="checkbox"/> YES</div> <div><input checked="" type="checkbox"/> NO</div> </div>																		
X. Check List <i>(To be filled in by applicant or agent)</i>	A. The application contains the following number of sheet(s) :- <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 60%;">1. Request.</td> <td style="width: 10%; text-align: center;">3</td> <td style="width: 30%;">sheets</td> </tr> <tr> <td>2. Description.</td> <td style="text-align: center;">45</td> <td>sheets</td> </tr> <tr> <td>3. Claim (s).</td> <td style="text-align: center;">3</td> <td>sheets</td> </tr> <tr> <td>4. Drawing (s).</td> <td style="text-align: center;">11</td> <td>sheets</td> </tr> <tr> <td>5. Abstract.</td> <td style="text-align: center;">1</td> <td>sheets</td> </tr> </table>	1. Request.	3	sheets	2. Description.	45	sheets	3. Claim (s).	3	sheets	4. Drawing (s).	11	sheets	5. Abstract.	1	sheets			
	1. Request.	3	sheets																
	2. Description.	45	sheets																
	3. Claim (s).	3	sheets																
	4. Drawing (s).	11	sheets																
	5. Abstract.	1	sheets																
	B. The application as filed is accompanied by :- <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 60%;">1. Priority document.</td> <td style="width: 10%;"></td> <td style="width: 30%;"></td> </tr> <tr> <td>2. Translation of priority document.</td> <td></td> <td></td> </tr> <tr> <td>3. Statement of Inventorship & right to grant</td> <td style="text-align: center;">X</td> <td></td> </tr> <tr> <td>4. International Exhibition Certificate.</td> <td></td> <td></td> </tr> </table>	1. Priority document.			2. Translation of priority document.			3. Statement of Inventorship & right to grant	X		4. International Exhibition Certificate.								
	1. Priority document.																		
	2. Translation of priority document.																		
	3. Statement of Inventorship & right to grant	X																	
4. International Exhibition Certificate.																			
XI. Signature (s) <i>(See note 10)</i>	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 30%;">Applicant (a)</td> <td colspan="2" style="text-align: center;"></td> </tr> <tr> <td>Date</td> <td colspan="2" style="text-align: center;">13 November 1998</td> </tr> <tr> <td>Applicant (b)</td> <td colspan="2"></td> </tr> <tr> <td>Date</td> <td colspan="2"></td> </tr> <tr> <td>Applicant (c)</td> <td colspan="2"></td> </tr> <tr> <td>Date</td> <td colspan="2"></td> </tr> </table>	Applicant (a)			Date	13 November 1998		Applicant (b)			Date			Applicant (c)			Date		
Applicant (a)																			
Date	13 November 1998																		
Applicant (b)																			
Date																			
Applicant (c)																			
Date																			

9804034-8

NOTES :

This form when completed should be brought or sent to the Registry of Patents together with the prescribed fee and 3 copies of the description of the invention, and of any drawings.

2. Enter the name and address of each applicant in the spaces provided at paragraph II. Names of individuals should be indicated in full and the surname or family name should be underlined. The names of all partners in a firm must be given in full. The place of residence of each individual should be furnished in the space provided. Bodies corporate should be designated by their corporate name and country of incorporation and, where appropriate, the state of incorporation within that country should be entered where provided. Where more than three applicants are to be named, the names and address of the fourth and any further applicants should be given on a separate sheet attached to this Form together with the signature of each of these further applicants.

3. The declaration of priority at paragraph III should state the date of the previous filing and the country in which it was made and indicate the file number, if available. When the application relied upon in an International Application or a regional patent application e.g. European patent application, one of the countries designated in that application [being one falling under the Patents (Convention Countries) Order] should be identified and the name of that country should be entered in the space provided.

4. Where the applicant or applicants is/are the sole inventor or the joint inventors, paragraph IV should be completed by marking the 'YES' Box in the declaration (a) and the 'NO' Box in the alternative statement (b). Where this is not the case, the 'NO' Box in declaration (a) should be marked and a statement will be required to be filed on Patents Form 8.

5. If the applicant has appointed an agent to act on his behalf, the agent's name should be indicated in the spaces available at paragraphs V.

6. An address for service in Singapore to which all documents may be sent must be stated at paragraph VI. It is recommended that a telephone number be provided if an agent is not appointed.

7. When an application is made by virtue of section 20(3), 26(6) or 47(4), the appropriate section should be identified at paragraph VIII and the number of the earlier application or patent granted thereon identified.

8. Where the applicant wishes an earlier disclosure of the invention by him at an International Exhibition to be disregarded in accordance with section (14(4)(c), then the 'YES' box at paragraph VIII should be marked. Otherwise the 'NO' box should be marked.

9. Where in disclosing the invention the application refers to one or more micro-organisms deposited with a depositary authority under the Budapest Treaty, then the 'YES' box at paragraph XI should be marked. Otherwise the 'NO' box should be marked.

10. Attention is drawn to rules 95 and 105 of the Patent Rules. Where there are more than three applicants, see also Note 2 above.

11. Applicants resident in Singapore are reminded that if the Registry of Patents considers that an application contains information the publication of which might be prejudicial to the defence of Singapore or the safety of the public, it may prohibit or restrict its publication or communication. Any person resident in Singapore and wishing to apply for patent protection in other countries must first obtain permission from the Singapore Registry of Patents unless they have already applied for a patent for the same invention in Singapore. In the latter case, no application should be made overseas until at least two months after the application has been filed in Singapore.

For Official Use

Application Filing Date : / /
Request received on : / /
Fee received on : / /
Amount : / /

* Cash / Cheque / Money Order No :

* Delete whichever is inapplicable.

9804034 - 8

SIGNAL PROCESSING APPARATUS AND METHOD

Background and Field of the Invention

5 This invention relates to a method of signal processing and apparatus therefor.

In many situations, observations are made of the output of a multiple input and multiple output system such as phase array
10 radar system, sonar array system or microphone array system, from which it is desired to recover the wanted signal alone with all the unwanted signals, including noise, cancelled or suppressed. For example, in a microphone array system for a speech recognition application, the objective is to enhance
15 the target speech signal in the presence of background noise and competing speakers.

The most widely used approach to noise or interference cancellation in a multiple channel case was suggested by
20 Widrow etc in "Adaptive Antenna Systems" Proc. IEEE, Vol.55 No.12, Dec. 1967 and "Signal Cancellation Phenomena in Antennas: causes and cures", IEEE Trans. Antennas Propag., Vol.AP30, May 1982. Also by L.J.Griffiths etc in " An Alternative Approach to Linearly Constrained Adaptive
25 Beamforming". IEEE Trans. Antennas Propag. VolAP30, 1982. In these and other similar approaches, the signal processing apparatus separates the observed signal into a primary channel which comprises both the target signal and the

interference signal and noise, and a secondary channel which comprises interference signal and noise alone. The interference signals and noise in the primary channel are estimated using an adaptive filter having the secondary
5 channel signal as input, the estimated interference and noise signal being subtracted from the primary channel to obtain the desired target signal.

There are two major drawbacks of the above approaches. The
10 first is that it is assumed that the secondary channel comprises interference signals and noise only. This assumption may not be correct in practice due to leakage of wanted signals into the secondary channel due to hardware imperfections and limited array dimension. The second is
15 that it is assumed that the interference signals and noise can be estimated accurately from the secondary channel. This assumption may also not be correct in practice because this will required a large number of degrees of freedom, this implying a very long filter and large array dimension. A very
20 long filter leads to other problems such as rate of convergence and instability.

The first drawback will lead to signal cancellation. This degrades the performance of the apparatus. Depending on the
25 input signal power, this degradation may be severe, leading to poor quality of the reconstructed speech because a portion of the desired signal is also cancelled by the filtering process. The second drawback will lead to poor interference

and noise cancellation especially low frequency interference signals the wavelengths of which are many times the dimension of the array.

5 It is an object of the invention to provide an improved signal processing apparatus and method.

Summary of the Invention

10 According to the invention in a first aspect, there is provided: signal processing apparatus comprising:

- 1) an array of sensors, each for receiving signals;
- 2) means for sampling and digitally converting the received signals; and
- 15 3) a digital processor for processing the digitally converted signals to provide an output signal, the processor having a first adaptive filter for enhancing the signals and a second adaptive filter for suppressing the signals, the operation of the filters being
- 20 controllable such that the first filter is operable to perform adaptive filtering to enhance the signals only when a target signal is deemed to be present and the second filter is operable to perform adaptive filtering to suppress the signals only when a target signal is
- 25 deemed not to be present.

According to the invention in a second aspect, there is provided: signal processing apparatus comprising:

- 1) an array of sensors, each for receiving signals;
- 2) means for sampling and digitally converting the received signals; and
- 3) a digital processor for processing the digitally converted signals to provide an output signal, the processor having at least one first adaptive filter to enhance a desired signal in a reference channel and provide undesired signals only in the other channel or channels, and a second adaptive filter for calculating a correlation time delay between signals of the array, the processor being operable to calculate a reverberation coefficient from the coefficients of the first and second filters.

15 According to the invention in a third aspect, there is provided: a method of calculating a spectrum from a coupled signal comprising the steps of:

- 1) deriving a target signal component S and an interference signal component I from the coupled signal;
- 20 2) transforming the target and interference signal components into respective frequency domain equivalents $F(S)$ and $F(I)$; and
- 3) constructing the spectrum $P(S)$ and $P(I)$ of at least one equivalent in accordance with:

$$25 \quad P(S) = \text{Real}(|F(S)|) + \text{Imag}(|F(S)|) + (F(S) * \text{conj}(F(S)) * R(s))$$

$$P(I) = \text{Real}(|F(I)|) + \text{Imag}(|F(I)|) + (F(I) * \text{conj}(F(I)) * R(i))$$

Where conj is the complex conjugate, Real and Imag refer to taking the absolute value of the real or imaginary

part of the frequency domain equivalent and $R(s)$, $R(i)$ are scalar adjustment factors.

According to the invention in a fourth aspect, there is provided: a method of calculating a reverberation coefficient from a plurality of signals received from respective sensors in respective signal channels of a sensor array comprising the steps of:

- 1) calculating a correlation time delay between
10 signals from a reference one of the channels and another one of the channels using an adaptive filter;
- 2) performing adaptive filtering, using a second adaptive filter, on the received signals; and
- 3) calculating a reverberation coefficient from the
15 filter coefficients of the first and second filters.

The second adaptive filter filters the received signals to provide a desired output. In the described embodiment, that output is an enhanced target signal and the calculated
20 reverberation coefficient thus relates to reverberation of the target signal. This aspect of the invention may be used, however, to calculate the reverberation coefficient of any other component of the received signal that the second adaptive filter is adapted to provide.

25

According to the invention in a fifth aspect, there is provided a method of signal processing of a signal having wanted and unwanted components comprising the steps of:

- 1) processing the signal in the time domain with at least one adaptive filter to enhance the wanted signal and/or reduce the unwanted signal,
- 2) transforming the thus processed signal to the
5 frequency domain; and
- 3) performing at least one unwanted signal reduction process in the frequency domain.

The invention extends to apparatus for performing the method
10 of the third to fifth aspects.

Each aspect of the invention is usable independently of the others, for example in other signal processing apparatus which need not include other features of this invention as
15 described.

The described embodiment of the invention discloses a method and apparatus to enhance an observed target signal from a predetermined or known direction of arrival. The apparatus
20 cancels and suppresses the unwanted signals and noise from their coupled observation by the apparatus. An approach is disclosed to enhance the target signal in a more realistic scenario where both the target signal and interference signal and noise are coupled in the observed signals. Further, no
25 assumption is made regarding the number or the direction of arrival of the interference signals.

The described embodiment includes an array of sensors e.g.

microphones each defining a corresponding signal channel, an array of receivers with preamplifiers, an array of analog to digital converters for digitally converting observed signals and a digital signal processor that processes the signals. 5 From the observed signals, the apparatus outputs an enhanced target signal and reduces the noise and interference signals. The apparatus allows a tradeoff between interference and noise suppression level and signal quality. No assumptions are make about the number of interference signals and the 10 characteristic of the noise.

The digital signal processor includes a first set of adaptive filters which act as a signal spatial filter using the first channel as a reference channel. This filter removes the 15 target signal "s" from the coupled signal and puts the remaining elements of the coupled signal, namely interference signals "u" and system noise "q" in an interference plus noise channel referred to as a Difference Channel. This filter also enhances the target signal "s" and 20 puts this in another channel, referred to as the Sum Channel. The Sum Channel consists of the enhanced target signal "s" and the interference signals "u" and noise "q".

The target signal "s" may not be removed completely from the 25 Difference Channel due to the sudden movement of the target speaker or of an object within the vicinity of the speaker, so this channel may contain some residue target signal on occasions which can lead to some signal cancellation.

However, the described embodiment greatly reduces this.

The signals from the Difference Channel are fed to a second adaptive filter set. This set of filters adaptively estimates
5 the interference signals and noise in the Sum Channel.

The estimated signals are fed to an Interference Signal and Noise Cancellation and Suppression Processor which cancels and suppresses the noise and interference signals from the
10 Sum Channel and outputs the enhanced target signal.

Updating of the parameters of the sets of adaptive filters is performed using a further processor termed a Preliminary Signal Parameters Estimator which receives the observed
15 signal and estimates the reverberation level of the signal, the system noise level, the signal level, estimate signal detection thresholds and the angle of arrival of the signal. This information is used by the decision processor to decide if any parameter update is required.

20

One application of the described embodiment of the invention is speech enhancement in a car environment where the direction of the target signal with respect to the system is known. Yet another application is speech input for speech
25 recognition applications. Again the direction of arrival of the signal is known.

Brief Description of the Drawings

An embodiment of the invention will now be described by way of example with reference to the accompanying drawings in which:

Fig.1 illustrate a general scenario where the invention may be used.

Fig.2 is a schematic illustration of a general digital signal processing system embodying the present invention.

Fig.3 is a system level block diagram of the described embodiment of Fig. 2.

Fig. 4a-c is a flow chart illustrating the operation of the embodiment of Fig. 3.

Fig 5 illustrates a typical plot of nonlinear energy of a channel and the established thresholds.

Fig.6(a) illustrates a wavefront arriving from 40 degree off-boresight direction

Fig 6(b) represents a time delay estimator using an adaptive filter

Fig 6(c) shows the impulse response of the filter indicates a wave front from the boresight direction.

Fig 7 illustrates the reverberation level of the received signal over time.

Fig 8 shows the schematic block diagram the four channel Adaptive Spatial Filter.

Fig 9 shows the schematic block diagram of the Adaptive Interference and Noise Estimator of Fig. 3.

Fig 10 shows an input signal buffer.

Fig 11 shows the use of a Hanning Window on overlapping blocks of signals.

Fig. 12 illustrates a sudden rise of noise level of the
5 nonlinear energy plot.

Fig. 13 illustrates the readjustment of the thresholds to reflect the sudden rise of noise energy level.

Detailed Description of the Embodiment of the Invention

10

FIG.1 illustrates schematically the operating environment of a signal processing apparatus 5 of the described embodiment of the invention, shown in a simplified example of a room. A target sound signal "s" emitted from a source s' in a known
15 direction impinging on a sensor array, such as a microphone array 10 of the apparatus 5, is coupled with other unwanted signals namely interference signals u1, u2 from other sources A,B, reflections of these signals ulr, u2r and the target signal's own reflected signal sr. These unwanted signals
20 cause interference and degrade the quality of the target signal "s" as received by the sensor array. The actual number of unwanted signals depends on the number of sources and room geometry but only three reflected (echo) paths and three direct paths are illustrated for simplicity of explanation.
25 The sensor array 10 is connected to processing circuitry 20-60 and there will be a noise input q associated with the circuitry which further degrades the target signal.

An embodiment of signal processing apparatus 5 is shown in FIG.2. The apparatus observes the environment with an array of four sensors such as microphones 10a-10d. Target and noise/interference sound signals are coupled when impinging on each of the sensors. The signals received by each of the sensors is amplified by an amplifier 20a-d and converted to a digital bitstream using an analogue to digital converter 30a-d. The bit streams are feed in parallel to the digital signal processor 40 to be processed digitally. The processor 10 provides an output signal to a digital to analogue converter 50 which is fed to a line amplifier 60 to provide the final analogue output.

FIG.3 shows the major functional blocks of the digital processor in more detail. The multiple input coupled signals are received by the four-channel microphone array 10a-10d, each of which forms a signal channel, with channel 10a being the reference channel. The received signals are passed to a receiver front end which provides the functions of amplifiers 20 and analogue to digital converters 30 in a single custom chip. The four channel digitized output signals are fed in parallel to the digital signal processor 40. The digital signal processor 40 comprises four sub-processors. They are (a) a Preliminary Signal Parameters Estimator and Decision Processor 42, (b) a Signal Adaptive Spatial Filter 44, (c) an Adaptive Linear Interference and Noise Estimator 46, and (d) an Adaptive Interference and Noise Cancellation and Suppression Processor 48. The basic signal flow is from

processor 42, to processor 44, to processor 46, to processor 48. These connections being represented by thick arrows in Fig. 3. The filtered signal S is output from processor 48. Decisions necessary for the operation of the processor 40 are
5 generally made by processor 42 which receives information from processors 44 - 48, makes decisions on the basis of that information and sends instructions to processors 44 - 48, through connections represented by thin arrows in Fig. 3.

10 It will be appreciated that the splitting of the processor 40 into the four component parts 42, 44, 46, 48 is essentially notional and is made to assist understanding of the operation of the processor. The processor 40 would in reality be embodied as a single multi-function digital processor
15 performing the functions described under control of a program with suitable memory and other peripherals.

A flowchart illustrating the operation of the processors is shown in Figs 4a-c and this will firstly be described
20 generally. A more detailed explanation of aspects of the processor operation will then follow.

The front end 20,30 processes samples of the signals received from array 10 at a predetermined sampling frequency, for
25 example 16kHz. The processor 42 includes an input buffer 43 that can hold N such samples for each of the four channels. Upon initialization, the apparatus collects a block of N/2 new signal samples for all the channels at step 500, so that

the buffer holds a block of $N/2$ new samples and a block of $N/2$ previous samples. The processor 42 then removes any DC from the new samples and preemphasizes or whitens the samples at step 502.

5

There then follows a short initialization period at step 504 in which the first 20 blocks of $N/2$ samples of signal after start-up are used to estimate the environment noise energy E_n and two detection thresholds, a noise threshold T_{n1} and a
10 signal threshold T_{s2} , are calculated by processor 42 from E_n using scaling factors. During this short period, an assumption is made that no target signals are present. These signals do, however, continue to be processed, so that an initial Bark Scale system noise value may be derived at step
15 570, below.

After this initialisation period, the energies and thresholds update automatically as described below. The samples from the reference channel 10a are used for this purpose although any
20 other channel could be used.

At step 500, with the total non-linear energy of the signal samples being calculated at step 506.

25 At step 508, it is determined if the signal energy E_s is greater than the signal threshold T_{s1} . If not, the environment noise E_n and the two thresholds are updated at step 510 using the new value of E_s calculated in step 506.

The Bark Scale system noise B_n (see below) is also similarly updated via point F. The routine then moves to point B. If so, the signal is passed to a threshold adjusting sub-routine 512-518.

5

Steps 514-518 is used to compensate for abrupt changes in environment noise level which may capture the thresholds. A time counter is used to determine if the signal level shows a steady state increase which would indicate an increase in noise, since the speech target signal will show considerable variation over time and thus can be distinguished. This is illustrated in Fig. 12 in which a signal noise level rises from an initial level to a new level which exceeds both thresholds. At step 512 a time counter C_c is incremented. At step 514 C_c is checked against a threshold T_{cc} . If the threshold is not reached, the program moves to step 520 described below. If the threshold is reached, the estimated noise energy E_n is then increased at step 516 by a multiple σ and E_n , T_{n1} and T_{n2} are updated at step 518. The effect of this is illustrated in Fig. 13. The counter is reset and updating ceases when the the signal energy E_r is less than the second threshold T_{r2} as tested at step 520 below.

A test is made at step 520 to see if the estimated energy E_r in the reference channel 10a exceeds the second threshold T_{n2} . If so, a candidate target signal is deemed to be present. The apparatus only wishes to process candidate target signals that impinge on the array 10 from a known direction normal to

25

the array, hereinafter referred to as the boresight direction, or from a limited angular departure therefrom, in this embodiment plus or minus 15 degrees. Therefore the next stage is to check for any signal arriving from this
5 direction.

At step 524 two coefficients are established, namely a correlation coefficient C_x and a correlation time delay T_d , which together provide an indication of the direction from
10 which the target signal arrived.

At step 526, two tests are conducted to determine if the candidate target signal is an actual target signal. First, the crosscorrelation coefficient C_x must exceed a
15 predetermined threshold T_c and, second, the size of the time delay coefficient must be less than a value θ indicating that the signal has impinged on the array within the predetermined angular range. If these conditions are not met, the signal is not regarded as a target signal and the routine passes to
20 point B. If the conditions are met, the routine passes to point A.

If at step 520, the estimated energy E_r in the reference channel 10a is found not to exceed the second threshold T_{n2} ,
25 the target signal is considered not to be present and the routine passes to point B via step 522 in which the counter C_c is reset. This is done since the second threshold at this point is above the level of the total signal energy E_r .

indicating that the threshold must be, consequently, above the environment noise energy level E_n and thus updating of E_n is no longer necessary.

5 Thus, the signal has, by points A and B, been preliminarily classified into a target signal (point A) or a noise signal (point B).

Following point A, the signal is subject to a further test at 10 steps 528-532. At step 528, it is determined if the filter coefficients W_{s_n} of filter 44 have yet been updated. If not, the subsequent steps 530, 532 are skipped, since these rely on the coefficients of filter 44 for calculation purposes. If so, a reverberation coefficient C_{rv} which provides a 15 measure of the degree of reverberation of the signal is calculated and at step 532 it is determined if C_{rv} exceeds a threshold T_{rv} . If so, this indicates an acceptable level of reverberation in the signal and the routine passes to step 534 (target signal filtering). If not, the signal joins the 20 path from point B to step 536 (non-target signal filtering).

The now confirmed target signal is fed to the Signal Adaptive Spatial Filter 44, the purpose of which is to enhance the target signal. The filter is instructed to perform adaptive 25 filtering at steps 534 and 538, in which the filter coefficients W_{s_n} are adapted to provide a "target signal plus noise" signal in the reference channel and "noise only" signals in the remaining channels using the Least Mean Square

(LMS) algorithm. The filter 44 output channel equivalent to the reference channel is for convenience referred to as the Sum Channel and the filter 44 output from the other channels, Difference Channels. The signal so processed will be, for
5 convenience, referred to as A'.

If the signal is considered to be a noise signal, the routine passes to step 536 in which the signals are passed through filter 44 without the filter coefficients being adapted, to
10 form the Sum and Difference channel signals. The signals so processed will be referred to for convenience as B'.

The effect of the filter 44 is to enhance the signal if this is identified as a target signal but not otherwise.

15

At step 540, the energy ratio R_{sd} between the Sum Channel and the Difference Channel is estimated by processor 42. At step 542 two tests are made. First, if the signals are A' signals from step 534, the routine passes to step 550. Second, for
20 those signals for which $E_r > T_{r2}$ (i.e., high energy level), R_{sd} is compared to a threshold T_{sd} . If the ratio is lower than T_{sd} , this indicates probable noise but if higher, this may indicate that there has been some leakage of the target signal into the Difference channel, indicating the presence
25 of a target signal after all. For such target signals the routine also passes to step 550. For all other non-target signals, the routine passes to step 544.

At steps 544-560, the signals are processed by the Adaptive Linear Interference and Noise Estimation Filter 46, the purpose of which is to reduce the unwanted signals. The filter 46, at step 544, is instructed to perform adaptive filtering on the non-target signals with the intention of adapting the filter coefficients to reducing the unwanted signal in the Sum channel to some small error value E_e .

To further prevent signal cancellation, the norm of the filter coefficients is calculated by processor 42 at step 546. If this norm exceeds a predetermined value $[T_{no}]$ at step 548, then the filter coefficients are scaled at step 549 to a reduced value.

In the alternative, at step 550, the target signals are fed to the filter 46 but this time, no adaptive filtering takes place, so the Sum and Difference signals pass through the filter.

An output of the Sum Channel signal without alteration is also passed through the filter 46.

The output signals from processor 46 are thus the Sum channel signal S_c (point C), filtered Difference signals D_c (point E) and an error signal e_c (point D). At step 562, a weighted average $S(t)$ of the error signal e_c and the Sum Channel signal is calculated and the signals from the Difference channels D_c are Summed to form a single signal $I(t)$. These

signals $S(t)$ and $I(t)$ are then collected for the new $N/2$ samples and the last $N/2$ samples from the previous block and a Hanning Window H_n is applied to the collected samples as shown in Fig. 10 to form vectors S_n and I_n . This is an overlapping technique with overlapping vectors S_n, I_n being formed from past and present blocks of $N/2$ samples continuously. This is illustrated in Fig. 11. A Fast Fourier Transform is then performed on the vectors S_n and I_n to transform the vectors into frequency domain equivalents S_f and I_f , at step 564.

At step 566 a modified spectrum is calculated for the transformed signals to provide "pseudo" spectrum values P_s and P_i and these values are warped into the same Bark Frequency Scale to provide Bark Frequency scaled values B_s and B_i at step 568.

The Bark value B_n of the system noise of the Sum Channel is updated at step 570 using B_s and the previous value of B_n , if the condition at step 508 is met (through path F). At start-up, B_n is initially calculated at this block whether or not the condition is met. At this time, there must be no target signal present, thus requiring a short initialization period after signal detection has begun, for this initial B_n value to be established.

A weighted combination B_y of B_n and B_i is then made at step 572 and this is combined with B_s to compute the Bark Scale

nonlinear gain G_e at step 574.

G_e is then unwarped to the normal frequency domain to provide a gain value G at step 578 and this is then used at step 580 to compute an output spectrum S_{out} using the signal spectrum S_e from step 564. This gain-adjusted spectrum suppresses both the interference signals, the environmental noise and system noise.

10 An inverse FFT is then performed on the spectrum S_{out} at step 582 and the output signal is then reconstructed from the overlapping signals using the overlap add procedure at step 584.

15 Major steps in the above described flowchart will now be described in more detail.

NonLinear Energy and Threshold Estimation and Updating (STEPS
506,510)

The processor 42 estimates the energy output from a reference channel. In the four channel example described, channel 10a is used as the reference channel.

N/2 samples of the digitized signal are buffered into a shift register to form a signal vector of the following form:

10

$$X_r = \begin{bmatrix} X(0) \\ X(1) \\ \cdot \\ \cdot \\ \cdot \\ X(J-1) \end{bmatrix} \dots A.1$$

Where $J = N/2$. The size of the vector depends on the resolution requirement. In the preferred embodiment, $J=256$ samples. The nonlinear energy of the vector is estimated using the following equation:

$$E_r = \frac{1}{J-2} \sum_{i=1}^{J-2} X(i)^2 - X(i+1) X(i-1) \dots A.2$$

When the system is initialized, the average system and environment noise energy is estimated using the first 20 blocks of signal. A first order recursive filter is used to carry out this task as shown below:.

$$E_n^{K+1} = \alpha E_n^K + (1-\alpha) E_r^{K+1} \dots A.3$$

Where the superscript K is the block number and α is an empirically chosen weight between zero and one. In this embodiment, $\alpha = 0.9$.

Once the noise energy E_n is obtained, the two signal detection thresholds T_{n1} and T_{n2} are established as follows:

$$T_{n1} = \delta_1 E_n \dots A.4$$

$$T_{n2} = \delta_2 E_n \dots A.5$$

δ_1 and δ_2 are scalar values that are used to select the thresholds so as to optimize signal detection and minimize false signal detection. As shown in Fig. 5, T_{n1} should be above the system noise level, with T_{n2} sufficient to be generally breached by the potential target signal. These thresholds may be found by trial and error. In this embodiment, $\delta_1=1.125$ and $\delta_2=1.8$ have been found to give good results.

Once the thresholds have been established, E_n may be updated after initialization in step 513 as follows:

$$\begin{aligned}
 & \text{If } E_r < T_{n1} \\
 & E_n = \alpha_n + (1-\alpha) E_r \\
 & \text{Else} \\
 & E_n = E_r
 \end{aligned}$$

...A.6

The updated thresholds may then be calculated according to equations A.4 and A.5.

Time Delay Estimation (T_d) (STEP 524)

5

FIG 6A illustrates a single wave front impinging on the sensor array. The wave front impinges on sensor 10d first (A as shown) and at a later time impinges on sensor 10a (A' as shown), after a time delay t_d . This is because the signal originates at an angle of 40 degrees from the boresight direction. If the signal originated from the boresight direction, the time delay t_d will have been zero ideally.

Time delay estimation of performed using a tapped delay line
 15 time delay estimator included in the processor 42 which is shown in Fig. 6B. The filter has a delay element 600 ,having a delay $Z^{-L/2}$, connected to the reference channel 10a and a tapped delay line filter 610 having a filter coefficient W_{td} connected to channel 10d. Delay element 600 provides a delay
 20 equal to half of that of the tapped delay line filter 610. The outputs from the delay element is $d(k)$ and from filter 610 is $d'(k)$. The Difference of these outputs is taken at element 620 providing an error signal $e(k)$ (where k is a time

index used for ease of illustration). The error is fed back to the filter 610. The Least Mean Squares (LMS) algorithm is used to adapt the filter coefficient W_{td} as follows:

$$W_{td}(k+1) = W_{td}(k) + 2\mu S_{10d}(k) e(k) \quad \dots B.1$$

5

$$W_{td}(k+1) = \begin{bmatrix} W_{td}^0(k+1) \\ W_{td}^1(k+1) \\ \cdot \\ \cdot \\ W_{td}^{L_0}(k+1) \end{bmatrix} \quad \dots B.2$$

$$S_{10d}(k) = \begin{bmatrix} S_{10d}^0(k) \\ S_{10d}^1(k) \\ \cdot \\ \cdot \\ S_{10d}^{L_0}(k) \end{bmatrix} \quad \dots B.3$$

$$e(k) = d(k) - d'(k) \quad \dots B.4$$

$$d'(k) = W_{td}(k)^T \cdot S_{10d}(k) \quad \dots B.5$$

$$\mu = \frac{\beta}{\|S_{10d}(k)\|} \quad \dots B.6$$

where β is a user selected convergence factor $0 < \beta \leq 2$, $\| \cdot \|$ denoted the norm of a vector, k is a time index, L_f is the filter length.

5 The impulse response of the tapped delay line filter 620 at the end of the adaptation is shown in Fig. 6c. The impulse response is measured and the position of the peak or the maximum value of the impulse response relative to origin 0 gives the time delay T_d between the two sensors which is also
 10 the angle of arrival of the signal. In the case shown, the peak lies at the centre indicating that the signal comes from the boresight direction ($T_d=0$). The threshold θ at step 506 is selected depending upon the assumed possible degree of departure from the boresight direction from which the target
 15 signal might come. In this embodiment, θ is equivalent to $\pm 15^\circ$.

Normalized Cross Correlation Estimation C_x (STEP 524)

20 The normalized crosscorrelation between the reference channel 10a and the most distant channel 10d is calculated as follows:

Samples of the signals from the reference channel 10a and
 25 channel 10d are buffered into shift registers X and Y where X is of length J samples and Y is of length K samples, where $J > K$, to form two independent vectors X_r and Y_r :

$$X_r = \begin{bmatrix} x_r(1) \\ x_r(2) \\ \cdot \\ \cdot \\ \cdot \\ x_r(J) \end{bmatrix} \quad \dots C.1$$

$$Y_r = \begin{bmatrix} y_r(1) \\ y_r(2) \\ \cdot \\ \cdot \\ \cdot \\ y_r(K) \end{bmatrix} \quad \dots C.2$$

A time delay between the signals is assumed, and to capture this Difference, J is made greater than K. The Difference is selected based on angle of interest. The normalized cross-correlation is then calculated as follows:

$$C_x(l) = \frac{Y_r^T * X_{rl}}{\|Y_r\| \|X_{rl}\|} \quad \dots C.3$$

$$\text{Where } \dots X_{rl} = \begin{bmatrix} X_r(l) \\ X_r(l+1) \\ \cdot \\ \cdot \\ \cdot \\ X_r(K+l-1) \end{bmatrix} \quad \dots C.4$$

10 Where ^T represents the transpose of the vector and $\| \|$ represent the norm of the vector and l is the correlation

lag. 1 is selected to span the delay of interest. For a sampling frequency of 16kHz and a spacing between sensors 10a, 10d of 18cm, the lag 1 is selected to be five samples for an angle of interest of 15°.

5

The threshold T_c is determined empirically. $T_c = 0.85$ is used in this embodiment.

Signal Reverberation Estimation C_{rv} (STEP 530)

10

The degree of reverberation of the received signal is calculated using the time delay estimator filter weight $[W_{td}]$ used in calculation of T_c above and the set of spatial filter weights $[W_{su}]$ from filter 44 (described below) as shown in the following equation:

$$C_{rv}^m = \frac{W_{td}^T W_{su}^m}{\|W_{td}\| \|W_{su}^m\|} \quad \dots D.1$$

Where T represents the transpose of the vector and M is the channel associated with the filter coefficient W_{su} . In this embodiment, three values for C_{rv} , one for each filter coefficient W_{su} are calculated. The largest is taken for subsequent processing.

The threshold T_{rv} used in step 506 is selected to ensure that the signal is selected as a target signal only when the level of reverberation is moderate, as illustrated in Fig. 7.

Adaptive Spatial Filter 44 (STEPS 534,536)

FIG.8 shows a block diagram of the Adaptive Linear Spatial Filter 44. The function of the filter is to separate the coupled target interference and noise signals into two types. The first, in a single output channel termed the Sum Channel, is an enhanced target signal having weakened interference and noise i.e. signals not from the target signal direction. The second, in the remaining channels termed Difference Channels, which in the four channel case comprise three separate outputs, aims to comprise interference and noise signals alone.

The objective is to adapt the filter coefficients of filter 44 in such a way so as to enhanced the target signal and output it in the Sum Channel and at the same time eliminate the target signal from the coupled signals and output them into the Difference Channels.

The adaptive filter elements in filter 44 act as linear spatial prediction filters that predict the signal in the reference channel whenever the target signal is present. The filter stops adapting when the signal is deemed to be absent.

The filter coefficients are updated whenever the conditions of steps 504 and 506 are met, namely:

- (i) The adaptive threshold detector detects the presence of signal;

- (ii) The time delay estimator indicates that the signal arrived from the predetermined angle;
- (iii) The normalized cross correlation of the signal exceeds the threshold; and
- 5 (iv) The reverberation level is low.

As illustrate in FIG.8, the digitized coupled signal X_0 from sensor 10a is fed through a digital delay element 710 of delay $Z^{-L_{su}/2}$. Digitized coupled signals X_1, X_2, X_3 from sensors 10 10b, 10c, 10d are fed to respective filter elements 712, 4, 6. The outputs from elements 710, 2, 4, 6 are Summed at Summing element 718, the output from the Summing element 718 being divided by four at divider element 719 to form the Sum channel output signal. The output from delay element 710 is 15 also subtracted from the outputs of the filters 712, 4, 6 at respective Difference elements 720, 2, 4, the output from each Difference element forming a respective Difference channel output signal, which is also fed back to the respective filter 712, 4, 6. The function of the delay element 710 is to 20 time align the signal from the reference channel 10a with the output from the filters 712, 4, 6.

The filter elements 712, 4, 6 adapt in parallel using the LMS algorithm given by Equations E.1..E.8 below, the output of 25 the Sum Channel being given by equation E.1 and the output from each Difference Channel being given by equation E.6:

$$\hat{S}_c(k) = (\bar{S}(k) + \bar{X}_0(k))/4 \quad \dots E.1$$

$$\text{Where: } \bar{S}(k) = \sum_{m=1}^{M-1} \bar{S}_m(k) \quad \dots E.2$$

$$\bar{S}_m(k) = (W_{su}^m(k))^T X_m(k) \quad \dots E.3$$

Where m is $0, 1, 2, \dots, M-1$, the number of channels, in this case 0..3 and T denotes the transpose of a vector.

5

$$X_m(k) = \begin{bmatrix} X_{1m}(k) \\ X_{2m}(k) \\ \cdot \\ \cdot \\ \cdot \\ X_{LSUm}(k) \end{bmatrix} \quad \dots E.4$$

$$W_{su}^m(k) = \begin{bmatrix} W_{su1}^m(k) \\ W_{su2}^m(k) \\ \cdot \\ \cdot \\ \cdot \\ W_{su\text{ }LSU}^m(k) \end{bmatrix} \quad \dots E.5$$

Where $X_m(k)$ and $W_{su}^m(k)$ are column vectors of dimension $L_{su} \times 1$.

The weight $W_{su}^m(k)$ is updated using the LMS algorithm as follows:

10 follows:

$$\hat{d}_{cm}(k) = \bar{X}_0(k) - \bar{S}_m(k) \quad \dots E.6$$

$$W_{su}^m(k+1) = W_{su}^m(k) + 2\mu^m X_m(k) \hat{d}_{cm}(k) \quad \dots E.7$$

$$\text{Where: } \mu^m = \frac{\beta}{\|X_m(k)\|} \quad \dots E.8$$

and where β is a user selected convergence factor $0 < \beta \leq 2$, $\| \cdot \|$ denoted the norm of a vector and k is a time index.

Adaptive Interference and Noise Estimation Filter 46 (STEPS 511, 512)

10 FIG.9 shows a schematic block diagram of the Adaptive Interference and Noise Estimation Filter 46. This filter estimates the noise and interference signals and subtracts them from the Sum Channel so as to derive an output with reduced noise and interference.

15

The filter 46 takes outputs from the Sum and Difference Channels of the filter 44 and feeds the Difference Channel Signals in parallel to another set of adaptive filter elements 750, 2, 4 and feeds the Sum Channel signal to a 20 corresponding delay element 756. The outputs from the three filter elements 750, 2, 4 are subtracted from the output from delay element 756 at Difference element 758 to form an error output e_c , which is also fed back to the filter elements

750,2,4. The output from filter element 756 is also passed directly as an output, as are the outputs from the three filter elements 750,2,4.

5 Again, the Least Mean Square algorithm (LMS) is used to adapt the filter coefficients W_{uq} as follows:

$$e_c(k) = \hat{S}_c(k) - \sum_{m=1}^{M-1} \hat{d}_{cm}(k) \quad \dots F.1$$

$$\text{where: } \hat{d}_{cm}(k) = W_{uq}^m(k)^T \cdot Y^m(k) \quad \dots F.2$$

$$Y^m(k) = \begin{bmatrix} \hat{d}_{c1m}(k) \\ \hat{d}_{c2m}(k) \\ . \\ . \\ \hat{d}_{cLuqm}(k) \end{bmatrix} \quad \dots F.3$$

10

$$W_{uq}^m(k+1) = W_{uq}^m(k) + 2\mu^m Y^m(k) e_c(k) \quad \dots F.4$$

$$\mu^m = \frac{\beta}{\|Y^m\|} \quad \dots F.5$$

and where β is a user selected convergence factor $0 < \beta \leq 2$ and where m is $0, 1, 2, \dots, M-1$, the number of channels, in this case is $0 \dots 3$.

Calculation of Energy Ratio R_{sd} (step 540)

This is performed as follows:

$$\hat{S}_c = \begin{bmatrix} \hat{S}_c(0) \\ \hat{S}_c(1) \\ \cdot \\ \cdot \\ \cdot \\ \hat{S}_c(J-1) \end{bmatrix} \quad \dots F.6$$

$$\hat{D}_c = \begin{bmatrix} \hat{d}_c(0) \\ \hat{d}_c(1) \\ \cdot \\ \cdot \\ \cdot \\ \hat{d}_c(J-1) \end{bmatrix} = \begin{bmatrix} \hat{d}_{c1}(0) \\ \hat{d}_{c1}(1) \\ \cdot \\ \cdot \\ \cdot \\ \hat{d}_{c1}(J-1) \end{bmatrix} + \begin{bmatrix} \hat{d}_{c2}(0) \\ \hat{d}_{c2}(1) \\ \cdot \\ \cdot \\ \cdot \\ \hat{d}_{c2}(J-1) \end{bmatrix} + \begin{bmatrix} \hat{d}_{c3}(0) \\ \hat{d}_{c3}(1) \\ \cdot \\ \cdot \\ \cdot \\ \hat{d}_{c3}(J-1) \end{bmatrix} \quad \dots F.7$$

$J=N/2$, the number of samples, in this embodiment 256.

$$E_{SUM} = \frac{1}{J-2} \sum_{j=1}^{J-2} \hat{S}_c(j)^2 - \hat{S}_c(j-1) \hat{S}_c(j+1) \quad \dots F.8$$

$$E_{DIF} = \frac{1}{3(J-2)} \sum_{j=1}^{J-2} \hat{d}_c(j)^2 - \hat{d}_c(j-1) \hat{d}_c(j+1) \quad \dots F.9$$

Where E_{SUM} is the sum channel energy and E_{DIF} is the difference channel energy.

$$R_{sd} = \frac{E_{SUM}}{E_{DIF}} \quad \dots F.10$$

The energy ratio between the Sum Channel and Difference Channel (R_{sd}) must not exceed a predetermined threshold. In the four channel case illustrated here the threshold is

determined to be about 1.5.

Calculation of Norm of filter coefficients (step 546)

5 The norms of the coefficients of filters 750,2,4 are also constrained to be smaller than a predetermined value. The rational for imposing this constraint is because the norm of the filter coefficients will be large if a target signal leaks into the Difference Channel. Scaling down the norm
10 value of the filter coefficients will reduce the effect of signal cancellation.

This is calculated as follows:

$$\text{If: } \|W_{uq}^m\| > T_{no} \dots G1$$

$$\text{Then: } W_{uq}^m = \frac{W_{uq}^m}{\|W_{uq}^m\|} * C_{no} \dots G.2$$

15 Where m is 1,2...M-1, the channels having W_{uq} filters. T_{no} is a predetermined threshold and C_{no} is a scaling factor, both of which can be estimated empirically.

The output e_c from equation F.1 is almost interference and
20 noise free in an ideal situation. However, in a realistic situation, this can not be achieved. This will cause signal cancellation that degrades the target signal quality or noise or interference will feed through and this will lead to degradation of the output signal to noise and interference

ratio. The signal cancellation problem is reduced in the described embodiment by use of the Adaptive Spatial Filter 44 which reduces the target signal leakage into the Difference Channel. However, in cases where the signal to noise and interference is very high, some target signal may still leak into these channels.

To further reduce the target signal cancellation problem and unwanted signal feed through to the output, The output signals from processor 46 are fed into the Adaptive NonLinear Interference and Noise Suppression Processor 48 as described below.

Adaptive NonLinear Interference and Noise Suppression
 15 Processor 48 (STEPS 562-584)

This processor processes input signals in the frequency domain coupled with the well-known overlap add block processing technique.

20

STEP 562: The output signal (e_c) and the Sum Channel output signal (S_c) combined as a weighted average as follows:

$$S(t) = W_1 S_c(t) + W_2 e_c(t) \quad \dots H.1$$

25 The weights (w_1, w_2) can be empirically chosen to minimize signal cancellation or improve unwanted signal suppression. In this embodiment, $w_1=w_2=0.5$.

This combined signal is buffered into a memory as illustrated in FIG.10. The buffer consists of $N/2$ of new samples and $N/2$ of old samples from the previous block. Similarly, the unwanted signals from the Difference Channel are summed in accordance with the following and buffered the same way as the Sum Channel:

$$I(t) = \sum_{i=1}^{M-1} D_{ci} \quad \dots H.2A$$

$$\text{Where: } D_{ci} = \begin{bmatrix} d_{ci}(0) \\ d_{ci}(1) \\ \cdot \\ \cdot \\ d_{ci}(J-1) \end{bmatrix} \quad \dots H.2B$$

Where $i=1,2\dots M-1$ and M is the number of channels, in this case $M=4$.

10

A Hanning Window is then applied to the N samples buffered signals as illustrated in FIG.11 expressed mathematically as follows:

$$S_h = \begin{bmatrix} S_{(t+1)} \\ S_{(t+2)} \\ \cdot \\ \cdot \\ S_{(t+N)} \end{bmatrix} \cdot H_r \quad \dots H.3$$

15

$$I_h = \begin{bmatrix} I_{(t+1)} \\ I_{(t+2)} \\ \vdots \\ I_{(t+N)} \end{bmatrix} \cdot H_n \quad \dots H.4$$

Where (H_n) is a Hanning Window of dimension N , N being the dimension of the buffer. The "dot" denotes point by point multiplication of the vectors. t is a time index.

Step 5.64: The resultant vectors $[S_h]$ and $[I_h]$ are transformed into the frequency domain using Fast Fourier Transform algorithm as illustrated in equations H.5 and H.6 below:

$$S_f = FFT(S_h) \quad \dots H.5$$

$$I_f = FFT(I_h) \quad \dots H.6$$

Step 566: A modified spectrum is then calculated, which is illustrated in Equations H.7 and H.8:

$$P_s = Real(|S_f|) + Imag(|S_f|) + (S_f * conj(S_f)) * r_s \quad \dots H.7$$

$$P_i = Real(|I_f|) + Imag(|I_f|) + (I_f * conj(I_f)) * r_i \quad \dots H.8$$

15 Where "Real" and "Imag" refer to taking the absolute values of the real and imaginary parts, r_s and r_i are scalars and

"Conj" denotes the complex conjugate.

The values of the scalars (r_s and r_i) control the tradeoff between unwanted signal suppression and signal distortion and may be determined empirically. (r_s and r_i) are calculated as $1/(2v_s)$ and $1/(2v_i)$ where v_s and v_i are scalars. In this embodiment, $v_s=v_i$ is chosen as 8 giving $r_s=r_i = 1/256$. As v_s, v_i reduce, the amount of suppression will increase.

10 Step 568: The Spectra (P_s) and (P_i) are warped into (Nb) critical bands using the Bark Frequency Scale [see Lawrence Rabiner and Bing Hwang Juang, Fundamentals of speech recognition, Prentice Hall 1993]. The number of Bark Critical bands depend on the sampling frequency used. For a sampling
15 of 16Khz, there will be $Nb = 25$ critical bands. The warped Pseudo Spectrum of (P_s) and (P_i) are denoted as (B_s) and (B_i).

Step 570: A Pseudo Spectrum of the system noise and environment noise is similarly computed and is denoted as
20 (B_n). B_n is first establish during system initialization as $B_n=B_s$ and continues to be updated when no target signal is detected (step 508) by the system i.e. any silence period. B_n is updated as follows:

```

                If  $E_r < T_{n1}$ 
25           $B_n = \alpha B_n + (1-\alpha) B_s$ 
                Else
           $B_n = B_n$ 

```

.....H.9

Steps 572,574: Using (B_s , B_i and B_n) a nonlinear technique is used to estimate a gain (G_n) as follows :

First the unwanted signal Pseudo Spectrum is combined with the system noise Pseudo Spectrum using an appropriate weighting function as illustrate in Equation J.1.

$$B_y = \Omega_1 B_i + \Omega_2 B_n \quad \dots J.1$$

Ω_1 and Ω_2 are weights which can be chosen empirically so as to maximize unwanted signals and noise suppression with minimize signal distortion.

Follow that a post signal to noise ratio is calculated using Equations J.2 and J.3 below:

$$R_{po} = \frac{B_s}{B_y} \quad \dots J.2$$

$$R_{pp} = R_{po} - I_c \quad \dots J.3$$

15

The division in equation J.2 means element by element division and not vector division. R_{po} and R_{pp} are column vectors of dimension $Nb*1$, Nb being the dimension of the Bark Scale Critical Frequency Band and I_c is a column unity vector of dimension $Nb*1$ as shown below:

$$R_{po} = \begin{bmatrix} I_{po(1)} \\ I_{po(2)} \\ \cdot \\ \cdot \\ I_{po(N_b)} \end{bmatrix} \quad \dots J.4$$

$$R_{pp} = \begin{bmatrix} I_{pp(1)} \\ I_{pp(2)} \\ \cdot \\ \cdot \\ I_{pp(N_b)} \end{bmatrix} \quad \dots J.5$$

$$I_c = \begin{bmatrix} 1 \\ 1 \\ \cdot \\ \cdot \\ \cdot \\ 1 \end{bmatrix} \quad \dots J.6$$

If any of the $r_{pp}(nb)$ elements of R_{pp} are less than zero, they are set equal to zero.

5 Using the Decision Direct Approach [see Y. Ephraim and D. Malah: Speech Enhancement Using Optimal NonLinear Spectrum Amplitude Estimation; Proc. IEEE International Conference Acoustics Speech and Signal Processing (Boston) 1983, pp1118-1121.], the a-priori signal to noise ratio R_{pr} is calculated
10 as follows:

$$R_{pr} = (1-\beta_i) * R_{pp} + \beta_i \frac{B_o}{B_y} \quad \dots J.7$$

The division in Equation J.7 means element by element division. B_o is a column vector of dimensions $Nb \times 1$ and denotes the output signal Bark Scale Pseudo Spectrum from the previous block $B_o = G_c \cdot B_s$ (see Eqn J.15) (B_o initially is zero). R_{pr} is also a column vector of dimension $Nb \times 1$. The value of β_i is given in Table 1 below:

i	β
1	0.01625
2	0.01225
3	0.245
4	0.49
5	0.98

TABLE 1

15

The value i is set equal to 1 on the onset of a signal and the β value is therefore equal to 0.01625. Then the i value will count from 1 to 5 on each new block of $N/2$ samples processed and stay at 5 until the signal is off. The i will start from 1 again at the next signal onset and the β is taken accordingly.

Instead of β being constant, in this embodiment β is made variable and starts at a small value at the onset of the signal to prevent suppression of the target signal and increases, preferably exponentially, to smooth R_{pr} .

From this, R_{rr} is calculated as follows:

$$R_{rr} = \frac{R_{pr}}{I_c + R_{pr}} \quad \dots J.8$$

The division in Equation J.8 is again element by element. R_{rr} is a column vector of dimension $Nb \times 1$.

5

From this, L_x is calculated:

$$L_x = R_{rr} \cdot R_{po} \quad \dots J.9$$

The value of L_x is limited to π (≈ 3.14). The multiplication in Equation J.9 means element by element multiplication. L_x is a column vector of dimension $Nb \times 1$ as shown below:

$$L_x = \begin{bmatrix} l_x(1) \\ l_x(2) \\ \cdot \\ \cdot \\ l_x(nb) \\ \cdot \\ \cdot \\ l_x(Nb) \end{bmatrix} \quad \dots J.10$$

A vector L_y of dimension $Nb \times 1$ is then defined as:

$$L_y = \begin{bmatrix} l_y(1) \\ l_y(2) \\ \cdot \\ \cdot \\ l_y(nb) \\ \cdot \\ \cdot \\ l_y(Nb) \end{bmatrix} \quad \dots J.11$$

Where $nb = 1, 2, \dots, Nb$. Then L_y is given as:

5

$$l_y(nb) = \exp\left(\frac{E(nb)}{2}\right) \quad \dots J.12$$

and

$$E(nb) = -0.57722 - \log(l_x(nb)) + l_x(nb) - (l_x(nb))^2/4 + l_x(nb)^3/8 - l_x(nb)^4/96 \dots$$

$\dots J.13$

10

$E(nb)$ is truncated to the desired accuracy. L_y can be obtained using a table look-up approach to reduce computational load.

Finally, the Gain G_b is calculated as follows:

$$G_b = R_{xx} \cdot L_y \quad \dots J.14$$

The "dot" again implies element by element multiplication.
 G_b is a column vector of dimension $Nb \times 1$ as shown:

$$G_b = \begin{bmatrix} g(1) \\ g(2) \\ \vdots \\ g(nb) \\ \vdots \\ g(Nb) \end{bmatrix} \quad \dots J.15$$

5

Step 578: As G_b is still in the Bark Frequency Scale, it is then unwarped back to the normal linear frequency scale of N dimensions. The unwarped G_b is denoted as G .

10 The output spectrum with unwanted signal suppression is given as:

$$\bar{S}_f = G \cdot S_f \quad \dots J.16$$

The "dot" again implies element by element multiplication.

15 Step 580: The recovered time domain signal is given by:

$$\bar{S}_t = \text{Real}(\text{IFFT}(\bar{S}_f)) \quad \dots J.17$$

IFFT denotes an Inverse Fast Fourier Transform, with only the Real part of the inverse transform being taken.

Step 584: Finally, the output time domain signal is obtained by overlap add with the previous block of output signal :

$$S_t = \begin{bmatrix} \bar{S}_t(1) \\ \bar{S}_t(2) \\ \cdot \\ \cdot \\ \bar{S}_t(N/2) \end{bmatrix} + \begin{bmatrix} Z_t(1) \\ Z_t(2) \\ \cdot \\ \cdot \\ Z_t(N/2) \end{bmatrix} \quad \dots J.18$$

10

$$\text{Where: } Z_t = \begin{bmatrix} \bar{S}_{t-1}(1+N/2) \\ \bar{S}_{t-1}(2+N/2) \\ \cdot \\ \cdot \\ \bar{S}_{t-1}(N) \end{bmatrix} \quad \dots J.19$$

The embodiment described is not to be construed as limitative. For example, there can be any number of channels from two upwards. Furthermore, any novel feature or combination of features disclosed is to be taken as forming an independent invention whether or not specifically claimed in the appendant claims of this application as initially filed.

CLAIMS

1. Signal processing apparatus comprising:
 - 1) an array of sensors, each for receiving signals;
 - 5 2) means for sampling and digitally converting the received signals;and
 - 3) a digital processor for processing the digitally converted signals to provide an output signal, the processor having a first adaptive filter for enhancing
10 the signals and a second adaptive filter for suppressing the signals, the operation of the filters being controllable such that the first filter is operable to perform adaptive filtering to enhance the signals only when a target signal is deemed to be present and the
15 second filter is operable to perform adaptive filtering to suppress the signals only when a target signal is deemed not to be present.

2. Signal processing apparatus comprising:
 - 20 1) an array of sensors, each for receiving signals;
 - 2) means for sampling and digitally converting the received signals;and
 - 3) a digital processor for processing the digitally converted signals to provide an output signal, the
25 processor having at least one first adaptive filter to enhance a desired signal in a reference channel and provide undesired signals only in the other channel or channels, and a second adaptive filter for calculating

a correlation time delay between signals of the array, the processor being operable to calculate a reverberation coefficient from the coefficients of the first and second filters.

5

3. A method of calculating a spectrum from a coupled signal comprising the steps of:

1) deriving a target signal component S and an interference signal component I from the coupled signal;

10

2) transforming the target and interference signal components into respective frequency domain equivalents $F(S)$ and $F(I)$; and

3) constructing the spectrum $P(S)$ and $P(I)$ of at least one equivalent in accordance with:

15

$$P(S) = \text{Real}(|F(S)|) + \text{Imag}(|F(S)|) + (F(S) * \text{conj}(F(S)) * R(s))$$

$$P(I) = \text{Real}(|F(I)|) + \text{Imag}(|F(I)|) + (F(I) * \text{conj}(F(I)) * R(i))$$

Where conj is the complex conjugate, Real and Imag refer to taking the absolute value of the real or imaginary part of the frequency domain equivalent and $R(s)$, $R(i)$

20

are scalar adjustment factors.

4. A method of calculating a reverberation coefficient from a plurality of signals received from respective sensors in respective signal channels of a sensor array comprising the 25 steps of:

1) calculating a correlation time delay between signals from a reference one of the channels and another one of the channels using an adaptive filter;

- 2) performing adaptive filtering, using a second adaptive filter, on the received signals; and
- 3) calculating a reverberation coefficient from the filter coefficients of the first and second filters.

5

5. A Method of Signal Processing of a signal having wanted and unwanted components comprising the steps of:

- 1) processing the signal in the time domain with at least one adaptive filter to enhance the wanted signal and/or reduce the unwanted signal,
- 2) transforming the thus processed signal to the frequency domain; and
- 3) performing at least one unwanted signal reduction process in the frequency domain.

10
15

6. Apparatus for performing the method of Claim 3 or Claim

4.

ABSTRACTSIGNAL PROCESSING APPARATUS


5

Signal processing apparatus is disclosed which comprises:


- 1) an array of sensors 10, each for receiving signals;
- 2) A/D converters 20,30 for sampling and digitally
10 converting the received signals;and
- 3) a digital processor 40 for processing the digitally
converted signals to provide an output signal, the
processor having a first adaptive filter 44 for
enhancing the signals and a second adaptive filter 46
15 for suppressing the signals, the operation of the
filters being controllable such that the first filter is
operable to enhance the signals only when a target
signal is deemed to be present and the second filter is
operable to suppress the signals only when a target
20 signal is deemed not to be present.

Fig 3.

FIG. 1



2/ =



(FIG 2)




Fig. 3.

4/11




Fig 4a

5/11




Fig 4b

6/11




Fig. 4c

7/11




FIG. 5.




FIG. 7

8/11




FIG 6A




FIG 6B






FIG 6C

9/11



CC/11




FIG. 11 Over-lap : block processing of a signal using Hanning window. The overlap in this case is 50%.




FIG. 10

11/11

